**4KX-PLUS INSTALLATION** Room Kit Plus and Inogeni 4KX-PLUS THE ADVANTAGE TO PLACING THE INOGENI AT THE TABLE is twofold: For USB Passthrough – with Inogeni at table 1) it is not necessary to extend USB 2) If more than one computer is used for USB Passthrough, the Lightware Line drawing or other switcher can also be at the table, simplifying wiring. Located at table Located at wall 3.5mm audio cable -Typical microphones Cisco Table Microphones Extended wiring CISCO QUAD CAMERA LINE - - 3.5MMTRS DMI W/ARC - - HDMI HDMI - - HDMI Codec Plus USB-A - - HOST wall-mounted 12VDC - - BARREL ETH - - CAM CTRL Presenter Camera O PTZ 4K Camera CODEC PLUS CISCO MIC 1 - - 3.5MM. 3.5MM. - - LINE OU  $\Rightarrow$ -Embedded audio-MIC 3 - - 3.5MM. 1080P VID 1 - - HDM HDMI - - 4K VIDEO 4KX-PLUS INOGENI K VID 2 - - HDMI HDMI - - 4K VIDEO HDMI - - VIDEO LOOF 5MM. - - HEADPHONES 4K VID 3 - - HDMI **LAPTOP** for Presentation DEVICE - - USB-B USB-A - - HOST and USB Passthrough INK-LOCAL 1 - - POE POWER - - MINI USB  $\rightarrow$ INK-LOCAL 2 - - ET ETH - - LAN Link-local network OUT 169.254.1.0/24 Loop through **NOTE**: If your Windows laptop has only PoE switch for second screen USB-C, you will need one of these adapters for HDMI and USB-A **COLOR KEY** CAT 5e or better Navigator UI Startech 3-IN-1 MULTIPORT FSR Digital Ribbon Cable ADAPTER p/n CDP2HDUACP2 NOTE: We recommend FSR Digital Ribbon Cable for long HDMI runs. If narrow conduit is a problem, Analog audio then traditional UTP extenders can be used. Link-local NOTE: MacBook FSR Digital Ribbon Cable or UTP extenders LANusers - you are accustomed to dongles © One that will work is Room Kit Plus the Apple USB-C Inogeni 4KX-PLUS Digital AV DRAWN BY Multiport Adapter ENRICO CONEDERA REVISED Ver 211210